

# STI Rex Plus®



ED-50

## PRODUCT OVERVIEW

In addition to the sound of a ferocious attack dog, Rex Plus offers the sounds of the rainforest. Choose the sound that suits you best: the continual sounds of the rainforest, or the option that allows you to use the rainforest sounds as an annunciator; the angry barking dog (for 15-20 seconds) followed by the sound of a siren or the angry barking dog that gets louder and more frequent as the intruder gets closer. Rex Plus is versatile and provides an excellent way to deter burglars, without the annoying problems of owning a real dog. With his electronic radar eyes, Rex Plus can “see” through thick doors, walls and glass. Once his cord is plugged into any standard 110 VAC electrical outlet, he’ll stay on duty around the clock.

## HOW IT WORKS

Any indoor location can be selected where you wish to detect movement; such as hidden behind the front door. Turn Rex Plus on and he begins detecting. When he detects movement (in attack dog mode), he begins to emit the ferocious barking sounds of a large, unhappy attack dog. The closer the intruder gets, the more frequent the barking becomes. As the intruder backs off, the barking decreases in frequency, stopping completely when movement is out of range. It’s very realistic and very effective. There’s also a variable volume control that enables the owner to adjust it to meet his or her individual needs.

## FEATURES

- Your choice of four sounds:
  - Continuous sound of the rainforest
  - Barking sound of a ferocious attack dog
  - Sounds of the rainforest to announce the arrival of visitors
  - Barking dog for 15-20 seconds, then siren
- Very realistic - barking gets more frequent as intruder gets closer.
- No installation required.
- Switches from the watchdog to the tranquil sounds of nature with the simple slide of a switch.
- Senses movement through walls, doors and glass.
- Variable distance sensitivity (up to 30') as well as volume control.
- Limited 90 day warranty.

# STI Rex Plus®

Dimensions and Technical Information

## MODEL AVAILABLE

ED-50 Rex Plus Unit

## WARRANTY

Limited 90 day warranty.

### Specifications:

Rex Plus consumes a minimal amount of electricity when he's in his "detecting" mode, but uses more power when barking.

Power Supply 12 VDC, 100 mA



Frequency 2.4 GHZ

Net Weight 2.2 lbs.(1.0 KG)

### Detection Efficiency:

Rex Plus' radar waves can detect intruders through a wide variety of materials with varying levels of efficiency. The following will serve as a guide.

| Material              | Effect On Range  |
|-----------------------|------------------|
| Glass                 | Slight reduction |
| Wooden Doors          | Slight reduction |
| Plaster Walls         | Medium reduction |
| Metal                 | Heavy reduction  |
| Curtains or Drapes    | Slight reduction |
| Fiberglass or Plastic | No reduction     |
| Paper Cartons         | Slight reduction |



**Safety Technology International, Inc.**

2306 Airport Road  
Waterford, Michigan  
48327, USA

Tel: 248-673-9898  
Fax: 248-673-1246  
Tollfree: 800-888-4784  
info@sti-usa.com  
www.sti-usa.com

Unit 49G Pipers Road  
Park Farm Industrial Estate  
Redditch, Worcestershire  
B98 0HU England

Tel: 44 (0) 1527 520 999  
Fax: 44 (0) 1527 501 999  
Free: 0800 085 1678 (UK)  
www.sti-europe.com